

FEATURES & BENEFITS

- A true variable transformer in a compact size
- Built-in Digital Voltage Readout
- A soft handle for hanging on lighting stands
- Full capacity breaker recessed to protect the toggle
- Indicator light and two female edisonon output
- Enclosure made from heavy-duty .090 black powder coated aluminum
- Eliminates the problems related to hand dimmers; SCR noise and imprecise settings



CATALOG NUMBER

121230

DESCRIPTION

Designed as an alternative to a 1K Variac when size and weight are considerations. The built in digital voltmeter allows the user to be aware of the exact voltage at all times.

TYPICAL APPLICATION

Great for practicals, china balls and small lighting fixtures. Rather than your typical variac sitting on the floor, you can easily hang this 1000W Mini-Yak on a lighting stand or C-stand.

MARKETS SERVED

Motion Picture and Television

Designed by a 728 Member & built in an IATSE Union shop

SPECIFICATIONS

Rating	8 Amp / 1000W Variable Transformer 0 – 140 VAC (120 VAC special order) 50 / 60 Hertz
Environmental Rating	NEMA 1 Enclosure
Input	5-15 plug / Male Edison
Output	5-15 Receptacle / 2 Female Edison
Overcurrent Protection	(1) 10 Amp full capacity hydraulic magnetic branch circuit breaker
Dimensions & Weight	8.5" L x 8.250" W x 6" H 15 lbs

