


FEATURES & BENEFITS

- 100 AMP Breaker - Yellow
- 200 AMP Breaker - Red
- Metering Test points – Input and Output Yellow and Red test points
- Bottom row of Cam-Locs are a Pass through
- Enclosure made from heavy-duty .090 black powder coated aluminum
- Courtesy NEMA L21-30 Circuit with push button breakers for protection



CATALOG NUMBER

180628

DESCRIPTION

The Mains Box is used to break down a 400A 3P Service down to 1-100A 3P Service and 1-200A 3P Services with Overcurrent Protection. The Medel Box also offers a set of Cam-Locs on the pass through on the bottom with a L21-30 courtesy circuit.

TYPICAL APPLICATION

Great for power distribution on 400A 3P Services.

MARKETS SERVED

Theatres, Conventions, Special Events, Motion Pictures and Television

SPECIFICATIONS

Rating	400AMP INPUT 3 Phase, 4 Pole, 5 Wire 120/208V 50 / 60 Hertz
Environmental Rating	NEMA I Enclosure
Input	Leviton ECT Series Cam-Locs 16R23
Output	Leviton ECT Series Cam-Locs 16R24 HBL2810 – NEMA L21-30
Overcurrent Protection	(1) 100A Square D Breaker JDL36100 (1) 200A Square D Breaker JDL36200 (3) 20A TE XB1A4A10-20 Push Button
Dimensions & Weight	18"L x 14"W x 12"H 50 lbs

