

FEATURES & BENEFITS

- A true variable transformer in a compact size
- Eliminates the problems related to hand dimmers; SCR noise and imprecise settings
- A soft handle for hanging on lighting stands
- Full capacity breaker recessed to protect the toggle
- Indicator light and two female edison output
- Enclosure made from heavy-duty .090 black powder coated aluminum



CATALOG NUMBER

121228

DESCRIPTION

Designed to replace the typical hardware-store hand dimmers and give you all the benefits a variac provides in a compact size.

TYPICAL APPLICATION

Great for practicals and china balls. Can power bulbs up to 213 photo floods. Small enough to hide on a set; hang on the back of a set wall or hang on a lighting stand.

MARKETS SERVED

Motion Picture and Television

OTHER INFORMATION

*** **OPTIONAL ACCESSORY** ***

Plug-in Digital Voltage Readout

Designed by a 728 Member & built in an IATSE Union shop



SPECIFICATIONS

Rating	2.5 Amp / 300W Variable Transformer 0 –120 VAC (140 VAC special order) 50 –60 Hertz
Environmental Rating	NEMA 1 Enclosure
Input	5-15 plug / Male Edison
Output	5-15 Receptacle / 2 Female Edison
Overcurrent Protection	(1) 2.5 Amp full capacity hydraulic magnetic branch circuit breaker
Dimensions & Weight	5.750”L x 5.625”W x 3.750”H 6 lbs

